

FDR Series

2.0-4.0GHz Input Frequency Doubler


Features

- Input Frequency: 2.0 – 4.0GHz
- Output Frequency: 4.0 –8.0GHz
- Conversion Loss: 14dB
- F0 Isolation: 25dB
- Input Drive Level: +12 to +18dBm
- No DC Power Required
- SMA Connector

Description

FDR-4-8 is a passive frequency doubler operates with input frequency range from 2.0 to 4.0GHz and output frequency range from 4.0 to 8.0GHz.

Picture





Electrical Specifications @ +25 °C, $Z_{IN} = Z_{OUT} = 50\Omega$, $P_{IN} = +15dBm$

Parameter	Unit	Min.	Typ.	Max.
Input Frequency Range F0	GHz	2.0		4.0
Output Frequency Range 2F0	GHz	4.0		8.0
Conversion Loss	dB		14	18
Input power P_{IN}	dBm	+12		+18
F0 Isolation *	dB	15	25	
3F0 Isolation *	dB	20	30	
Input VSWR S_{11} @ 3.0GHz			2.2:1	3.0:1
Output VSWR S_{22} @ 6.0GHz			1.5:1	2.5:1

* Isolation with respect to output power level of 2F0



FDR Series

2.0-4.0GHz Input Frequency Doubler



FDR Series


2.0-4.0GHz Input Frequency Doubler




FDR Series

2.0-4.0GHz Input Frequency Doubler

Return Loss S11 vs Frequency



Return Loss S22 vs Frequency



FDR Series

2.0-4.0GHz Input Frequency Doubler


Absolute Maximum Ratings

Parameter	Absolute Maximum
RF Input Power	+27dBm
Operating Temperature	-40 °C to +85 °C
Storage Temperature	-65 °C to +150 °C

ESD Sensitive Material



Outline



	A	B	C	D	E	F	G
Inch	1.250	1.250	1.000	0.625	1.000	0.563	0.250
mm	31.75	31.75	25.40	15.88	25.40	14.29	6.35